



MP12 Parts list (1)

All the components in this list are included in the kit, except the transformers and the DOA which are optional
 Tous les composants de cette liste sont inclus dans le kit sauf les transformateurs et l' AOD qui sont optionnels

Reference	Value	Qty	Description	Marking	Dim (2)	Manuf.
R20, R33, R34	47R	3	Resistor 1%, 1/4W	YEL VIO BLK BRN		
R12	68R	1	Resistor 1%, 1/4W	BLU GRY BLK GLD BRN		
R16, R17	100R	2	Resistor 1%, 1/4W	BRN BLK BRN BRN		
R3, R4, R7, R29	150R	4	Resistor 1%, 1/4W	BRN GRN BRN BRN		
R35, R36	180R	2	Resistor 1%, 1/4W	BRN GRY BRN BRN		
R21	330R	1	Resistor 1%, 1/4W	ORG ORG BRN BRN		
R13	470R	1	Resistor 1%, 1/4W	YEL VIO BRN BRN		
R5, R6	560R	2	Resistor 1%, 1/4W	GRN BLU BRN BRN		
R38	820R	1	Resistor 1%, 1/4W	GRY RED BLK BLK BRN		
R31	1K2	1	Resistor 1%, 1/4W	BRN RED BLK BRN BRN		
RL2	2K7	1	Resistor 1%, 1/4W	RED VIO RED BRN		
R1, R2	6K8	2	Resistor 1%, 1/4W matched to 1%	BLU GRY RED BRN		
R14, R27, R32	15K	3	Resistor 1%, 1/4W	BRN GRN BLK RED BRN		
R8	33K	1	Resistor 1%, 1/4W	ORG ORG BLK RED BRN		
R26, R28	47K	2	Resistor 1%, 1/4W	YEL VIO BLK RED BRN		
R37	56K	1	Resistor 1%, 1/4W	GRN BLU ORG BRN		
R23, R25, R30	100K	3	Resistor 1%, 1/4W	BRN BLK YEL BRN		
R22, R24	220K	2	Resistor 1%, 1/4W	RED RED YEL BRN		
R18, R19	560K	2	Resistor 1%, 1/4W	GRN BLU YEL BRN		
R9	1M	1	Resistor 1%, 1/4W	BRN BLK GRN BRN		
R10, R11, R15	2M2	3	Resistor 5%, 1/4W	RED RED GRN GLD		
C9	100p-100V	1	Capacitor Film (not used with SK47)	100	R5	Wima
C2, C23, C24, C25	100n-100V	4	Capacitor Ceramic	104	R5	
C4, C6, C10, C11, C15	470n-100V	5	Capacitor Film	u47	R7.5	Epcos
C16	1u-50V	1	Capacitor Electro Low ESR, 105°		D5R2	Nichicon
C12, C13, C17, C18, C21, C22	33u-35V	6	Capacitor Electro Low ESR, 105°		D5R2	Nichicon
C7, C8	150u-35V	2	Capacitor Electro Low ESR, 105°		D8R3.5	Nichicon
C1, C3	180u-63V	2	Capacitor Electro Low ESR, 105°		D10R5	Nichicon
C14	1200u-16V	1	Capacitor Electro Low ESR, 105°		D10R5	Nichicon
C5	1000u-6V3	1	Capacitor Electro, Bipolar		D10R5	Nichicon
C19, C20	2200u-35V	2	Capacitor Electro Low ESR, 105°		D16R7.5	Nichicon
L1	6uH	1	Inductor			
D1, D2, D3, D4, D9	1N914	5	Signal diode	914 or 4148		
D6, D7	1N4004	2	Rectifier diode	1N4004		
D8	Z7V5-0.5W	1	Zener diode	BZX55C 7V5		
D5	Red/Green	1	2 colors LED, 2 pins		D3	
Q1	TIP126	1	PNP power darlington	TIP126		

U1	OP07	1	Low offset Op-Amp	OP07CP		
U2	TL074CN	1	Quad Op-Amp	TL074CN		
U3	LM317	1	Positive voltage regulator	LM317T or TS317		
U4	LM337	1	Negative voltage regulator	LM337T		
A1		1	Discrete Operational Amplifier			
SW1	SPDT	1	Min toggle switch on/on, short lever, red cap			
SW2	DPDT	1	Min toggle switch on/on			
SW3	DPDT	1	Min toggle switch on/off/on			
Output	NC3MDL	1	XLR socket 3pins male			Neutrik
Input	NC3FDL	1	XLR socket 3pins fem.			Neutrik
CN1, CN2	2 term	2	PCB terminal blocks		R5	
CN3	26pins	1	IDC box header			
JMP4	1x2 pins	1	SIL pin header		R2.54	
JMP3	1x3 pins	1	SIL pin header		R2.54	
JMP1, JMP5	1x4 pins	2	SIL pin header		R2.54	
Jumper		4	Jumper		R2.54	
DOA socket		7	Pin socket		D1	
TP1, TP2, TP3		3	Test pin		D1	
OP07 socket	8 pins	1	IC socket			
P2	2x1KA	1	Potentiometer	1KA	L18	Omeg
P1	1KC+20KC	1	Potentiometer	1KC-22KC	L16	Omeg
P5, P6	5K	2	Trimmer pot	502 or 5K		
P3, P4	20K	2	Trimmer pot	203 or 20K		
RLY1, RLY2		2	Relay DPDT 24V	Black case		
U1, U2, Q1heatsinks	21 K/W	3	Heatsink TO220			
Main PCB		1	PCB		92x200	
Gain knob		1	Knob		D23	
Gain knob		1	Cap		D23	
Pad knob		1	Knob		D16	
Pad knob		1	Cap		D16	
Front pannel		1	MP12 front pannel			
Front pannel assembly	M3x6	2	Stainless st. screw countersunk			
XLR Assembly	M3x10	4	Screw pan head			
Transfo. Assembly	M3x25	2	Screw pan head			
Transfo. assembly	M3	6	Metal washer			
PCB, Transfo, XLR assembly	M3	10	Self locking nut			
XLR connect		2	Flexible wire 0.5mm2, Blue		8cm	
XLR connect		2	Flexible wire 0.5mm2, Red		8cm	
XLR GND connect		2	Tinned copper wire D0.9mm (20wg)		3cm	
Input transformer option : Cinemag CMMI-8-PCA (1:8)						
T1	CMMI-8-PCA	1	Mic input transformer 1:8			Cinemag
RL1	82K	1	Resistor 1%, 1/4W	GRY RED ORG BRN		

RZ1	10K	1	Resistor 1%, 1/4W	BRN BLK ORG BRN		
CZ1	22p-100V	1	Capacitor Ceramic	22	R2.5	
Transfo. assembly		1	Double sided adhesive tape		2cm	
Input transformer option : Lundhal LL1538 (1:5)						
T1	LL1538	1	Mic input transformer 1:5			Lundhal
RL1	33K	1	Resistor 1%, 1/4W	ORG ORG BLK RED BRN		
Transfo. assembly		1	Double sided adhesive tape		2cm	
Input transformer option : Lundhal LL1538 (1:2.5)						
T1	LL1538	1	Mic input transformer 1:2.5			Lundhal
RL1	8K2	1	Resistor 1%, 1/4W	GRY RED RED BRN		
Transfo. assembly		1	Double sided adhesive tape		2cm	
Input transformer option : OEP (1:6.5)						
T1	A262A3E	1	Mic input transformer 1:6.5			OEP
RL1	33K	1	Resistor 1%, 1/4W	ORG ORG BLK RED BRN		
RZ1	47K	1	Resistor 1%, 1/4W	YEL VIO BLK RED BRN		
CZ1	220p	1	Capacitor Film	220	R5	Wima
Transfo. assembly		1	Double sided adhesive tape		2cm	
Input transformer option : OEP (1:3.2)						
T1	A262A3E	1	Mic input transformer 1:3.2			OEP
RL1	10K	1	Resistor 1%, 1/4W	BRN BLK ORG BRN		
RZ1	22K	1	Resistor 1%, 1/4W	RED RED ORG BRN		
CZ1	330p	1	Capacitor Film	330	R5	Wima
Transfo. assembly		1	Double sided adhesive tape		2cm	
Output transformer option : Cinemag CMOQ-2S						
T2	CMOQ-2S	1	Line output Transformer 1+1:1+1			Cinemag
Output transformer option : Cinemag CMOB-2H						
T2	CMOB-2H	1	Line output Transformer 1:1			Cinemag
Output transformer option : Edcor WSM600/600						
T2	WSM600/600	1	Line output Transformer 1:1			Edcor
Transfo. assembly	M3	2	Nut			
Transfo. Connect		1	Flexible wire 0.5mm2, Blue		7cm	
Transfo. Connect		1	Flexible wire 0.5mm2, Red		7cm	
Transfo. Connect		1	Flexible wire 0.5mm2, Yellow		10cm	
Transfo. Connect		1	Flexible wire 0.5mm2, Black		10cm	
Output transformer option : Lundhal LL1517						
T2	LL1517	1	Line output Transformer 1+1:1+1			Lundhal
Transfo. assembly		1	Double sided adhesive tape		2cm	

(1) Data can be changed without notice

(2) Rx : spacing between leads or pins=x, Dx : diameter=x, Lx : Pot spindle length=x, Dimensions in mm unless differently stated

Schematic Rev 1.2

PCB Rev 1.2

Last modified : 15/05/2008